



N-BM300 W SIZE MATTERS



Finger



RFID



WiFi



LAN



USB



Access Control

Fingerprint Time Attendance and Access Control

Storage Capacity

Finger Capacity	3000
Card Capacity	3000
Max Users	3000
Password	3000
Log Capacity	1,50,000



N-BM300 W

"N -BM300, use the device to secure and manage entries and exit places where the space available is small."

Features

High-Speed and Accurate Fingerprint Identification

Fingerprint, Card, Password authentication

output relay for door open.

Good adaptation for dry, moist and rough fingerprints.

Supremely low Electric energy consumption.

Highly reliable and durable.

Comprehensive software development kit(SDK) is available for development and integration.

N-BM300 W

Communication Interface

Communication	WiFi, TCP/IP, USB
---------------	-------------------

Biometric

Push Data	YES (Optional)
Sensor type	500 DPI
FAR	0.00001%
FRR	0.001%
Verification Time	<=1 second
RF card options	125kHz EM (Standard) / 13.56MHz Mifare (Optional)

Audio/Visual

Display	Capacitive Touch Screen
Voice instruction	16-bit Hi-Fi voice & sound indication
Language	English

Access control

Wiegand in & out	YES
Relay	YES
Support	Wiegand Reader, Remote, Push Button, No Touch
Standard Access Control Function	255 Time Zone, Anti-passback Multi-identification Verify mode

Power & Environment

Operating Temperature	0°C ~ 50°C
Power	12V DC / 2A
Dimension (L*H*W)	150 x 150 x 35 mm



Accepts moist and rough Finger



Accepts Color & Mahendi Finger



WiFi, TCP/IP, USB



Unaffected by High
Temperatures 0° ~ 50°

Software

Desktop, Web, Cloud



Time Attendance



Access Control



Employee Self Service



Mobile App

Disclaimer : Brief specifications are mentioned here. specification may change without prior notice. Customers are advised to check with us before purchase. Actual product may differ slightly to that depicted for ongoing product development.

Certified by    

www.biomaxsecurity.com

Connect with us on



BiomaxOfficial



BioMax Security



biomaxsecurity



BioMax Access Control